

5 in 1 INTERCHANGEABLE

25HK  
SERIES

# DESK TOP/PLUG TOP POWER SUPPLIES



- Can be used for either Desk Top or Plug Top applications
- Fig 8 inlet Desk Top with Interchangeable AC Plug Top Converters
- Universal input 90~264V AC 50/60Hz
- Over Voltage Protected
- Approvals to UL, TUV, SAA, PSE, LPS, CE, RoHS & CEC IV compliant
- 3~30V Output models available
- 0 ~ 40°C Operating Temperature
- Available with a wide variety of output connectors

Call us on **0845 260 3400**

[www.idealpower.co.uk](http://www.idealpower.co.uk)



**IDEAL POWER**  
IDEAL POWER SOLUTIONS

Acorn House, Tree Beech Enterprise  
Park, Gunn, Barnstaple, Devon,  
ENGLAND EX32 7NZ

BROADCASTING

MEDICAL

COMMERCIAL

MISSION CRITICAL

TELECOM

INSTRUMENTATION



SERIES	O/P (V)	O/P (A)	POWER (W)	APPROVALS
<b>25HK - CP SERIES</b>	<b>DIMENSIONS 77x47x37mm INPUT SOCKET 2 Pin (C8)</b>			
25HK-CP09-A03	3.0V	3.0A (max.)	9W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP10-A033	3.3V	3.0A (max.)	10W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP09-A04	4.0V	2.2A (max.)	9W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP09-A045	4.5V	2.0A (max.)	9W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP13-A05	5.0V	2.5A (max.)	12.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP10-A06	6.0V	1.75A (max.)	10.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP10-A07	7.0V	1.5A (max.)	10.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP10-A075	7.5V	1.4A (max.)	10.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP10-A08	8.0V	1.3A (max.)	10.4W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP10-A085	8.5V	1.25A (max.)	10.6W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP11-A09	9.0V	1.2A (max.)	10.8W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP11-A10	10.0V	1.15A (max.)	11.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP11-A11	11.0V	1.05A (max.)	11.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A12	12.0V	1.0A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A13	13.0V	0.9A (max.)	11.7W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A138	13.8V	0.85A (max.)	11.7W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A15	15V	0.8A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A16	16V	0.75A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A18	18V	0.67A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A20	20V	0.6A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A21	21V	0.57A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A22	22V	0.55A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-CP12-A24	24V	0.5A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
<b>25HK - IP SERIES</b>	<b>DIMENSIONS 77x47x37mm INPUT SOCKET 2 Pin (C8)</b>			
25HK-IP12-A04	4.0V	3.0A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP13-A045	4.5V	3.0A (max.)	13.5W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP15-A05	5.0V	3.0A (max.)	15W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP12-A06	6.0V	2.0A (max.)	12W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP14-A07	7.0V	2.0A (max.)	14W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP15-A075	7.5V	2.0A (max.)	15W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP16-A08	8.0V	2.0A (max.)	16W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP17-A085	8.5V	2.0A (max.)	17W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A09	9.0V	2.0A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A10	10.0V	1.8A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A11	11.0V	1.63A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A12	12.0V	1.5A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS

SERIES	O/P (V)	O/P (A)	POWER (W)	APPROVALS
25HK-IP18-A13	13.0V	1.38A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A138	13.8V	1.3A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A15	15V	1.2A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A16	16V	1.1A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A18	18V	1.0A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A20	20V	0.9A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A21	21V	0.85A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A22	22V	0.8A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A24	24V	0.75A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A27	27V	0.66A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
25HK-IP18-A30	30V	0.6A (max.)	18W	UL/cUL/TUV/CB/PSE/SAA/LPS/CE/RoHS
<b>25HK - HP SERIES</b>	<b>DIMENSIONS 89x56x41mm INPUT SOCKET 2 Pin (C8)</b>			
25HK-HP12-A03	3.0V	4.0A (max.)	12W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP13-A033	3.3V	4.0A (max.)	13.2W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP16-A04	4.0V	4.0A (max.)	16W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP18-A045	4.5V	4.0A (max.)	18W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP20-A05	5.0V	4.0A (max.)	20W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP21-A06	6.0V	3.5A (max.)	21W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP24-A07	7.0V	3.5A (max.)	24.5W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP23-A075	7.5V	3.0A (max.)	22.5W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP20-A08	8.0V	2.5A (max.)	20W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP21-A085	8.5V	2.5A (max.)	21W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP23-A09	9.0V	2.5A (max.)	22.5W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP25-A10	10.0V	2.5A (max.)	25W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP28-A11	11.0V	2.5A (max.)	27.5W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A12	12.0V	2.5A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A13	13.0V	2.3A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A138	13.8V	2.17A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A15	15V	2.0A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A16	16V	1.87A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A18	18V	1.66A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A20	20V	1.5A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A21	21V	1.47A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A22	22V	1.42A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A24	24V	1.25A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A27	27V	1.1A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS
25HK-HP30-A30	30V	1.0A (max.)	30W	UL/cUL/TUV/CB/PSE/LPS/CE/RoHS

■ Please advise output voltage and connector required

■ Also Available from   

Please visit our website [www.idealpower.co.uk](http://www.idealpower.co.uk)  
for more information or alternatively contact us on **0845 260 3400**  
or fax this page with your details to **0845 260 3401**



**IDEAL POWER**  
IDEAL POWER SOLUTIONS

NAME.....

COM.....

CON.....



**POWER**

IDEAL REQUIREMENTS